

23 dBm Dual Wide Band Cell Phone Repeater with Display

- 99% pass customs clearance,Hutsin have many certificates,such as CE,RoHS,FCC,etc....
- 100% solve mobile cell phone weak signal problem.
- Signal booster able to increase signal coverage, decrease mobile phone radiation, and increase mobile phone battery lifespan.
- Hutsin's signal repeater easy to cover over 1000-3000m2 and easy to install.
- Dual band support two frequency bands high power 2g 3g 4g home signal booster.
- ALC function,auto control of output power for stable coverage.
- Average using life is over 5 years and one year warranty.

Specifications :

Part No.	6010100003
Frequency Bands	Any two in band 1, 2, 3, 4, 5, 7, 8, 20, 25, 28, 66
Bandwidth	Full Bandwidth
Gain	UL 73dB , DL 73dB
Output Power	UL 23dBm, DL 23dBm
Gain Attenuate	1~31dB, Step of 1dB
ALC Control Range	≥25dB
VSWR	≤2.0
Spurious Emission	≤-36dBm @ 9KHz~1GHz, ≤-30dBm @ 1GHz~12.75GHz
ACRR	Fully comply with 3GPP
EVM	Fully comply with 3GPP
PCDE	Fully comply with 3GPP
Noise Figure	≤8.0dB
Group Delay	≤1.5μs
Power Supply	DC 12V /3A
Dimension	292*140*48mm
Weight	<1.8kg

Product Image:



Application diagram:

